

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Currently amended) An optical repeater system, comprising:

a plurality of optical repeaters coupled in series, each configured to receive and convert a corresponding different radio frequency (RF) analog signal to a first baseband digital electrical signal, sum the first baseband digital electrical signal and a second baseband digital electrical signal transmitted from a previous optical repeater in the ~~series to series,~~ and generate an optical output signal from the summed first baseband digital electrical signal and second baseband digital electrical signal; and

a base station configured to receive and demodulate the optical output signal of a last one of the plurality of optical repeaters in the series.
2. (Previously Presented) The system of claim 1, wherein the second baseband digital electrical signal transmitted from the previous optical repeater in the series is a previously summed signal.

3. (Original) The system of claim 1, wherein the series connection comprises a daisy chain connection.

4. (Previously Presented) The system of claim 1, wherein each optical repeater comprises:

a band-pass filter (BPF) configured to filter the received RF analog signal and output a filtered RF analog signal;

an amplifier configured to amplify the filtered RF analog signal with a gain and output an amplified RF analog signal;

a frequency converter configured to convert the amplified RF analog signal to the first baseband digital electrical signal;

a digital delay device configured to delay the first baseband digital electrical signal;

an Optical signal to Electrical signal converter (O/E converter) configured to convert a baseband digital optical signal received from the previous optical repeater to the second baseband digital electrical signal;

a digital summer configured to sum the first baseband digital electrical signal and the second baseband digital electrical signal; and

an Electrical signal to Optical signal digital converter (E/O converter) configured to convert a summed signal outputted from the digital summer to the optical output signal.

5. (Previously Presented) The system of claim 4, wherein the digital delay device delays the first baseband digital electrical signal to match a round trip delay time of each optical repeater.

6. (Previously Presented) The system of claim 4, further comprising an automatic gain control (AGC) circuit configured to control the gain of the amplifier, wherein the AGC circuit controls the amplifier to maintain a uniform amplitude of the amplified RF analog signal.

7. (Previously Presented) The system of claim 1, wherein each of the plurality of optical repeaters is coupled with at least one other of the plurality of optical repeaters by an optical link.

8. (Previously Presented) The system of claim 7, wherein the optical link comprises an optical cable.

9. (Original) The apparatus of claim 1, wherein the last optical repeater is coupled with the base station by an optical cable.

10. (Previously Presented) A method for receiving in an optical repeater, comprising:

receiving and converting a first radio frequency (RF) analog signal to a first baseband digital signal in a first repeater;

receiving and converting a second RF analog signal to a second baseband digital signal in a second repeater connected in series with the first repeater;

summing the first baseband digital signal with the second baseband digital signal received from the second repeater;

converting an output of the summed signal to an optical output signal; and
transmitting the optical output signal to a base station.

11. (Original) The method of claim 10, further comprising:

receiving the optical output signal in the base station;

converting the received optical output signal to an electrical signal; and

demodulating the converted electrical signal.

12. (Previously Presented) The method of claim 10, wherein converting the RF analog signals comprises amplifying the RF analog signals with a prescribed gain in accordance with an automatic gain control circuit to maintain a prescribed amplitude of the amplified RF analog signals.

13. (Original) The method of claim 10, wherein the first baseband digital signal is delayed to match a round trip delay time of at least one other optical repeater coupled in series.

14. (Canceled)

15. (Original) The method of claim 10, wherein the second baseband digital signal from the second repeater is a sum of baseband digital signals from a plurality of optical repeaters.

16. (Original) The method of claim 10, wherein the optical output signal is transmitted to the base station over an optical cable.

17. (Previously Presented) A method for receiving in a first optical repeater, comprising:

receiving and amplifying a radio frequency (RF) analog signal;

converting the amplified RF analog signal to a first baseband digital signal;

delaying the first baseband digital signal;

summing the delayed first baseband digital signal and a second baseband digital signal received from a second optical repeater to generate an electrical output signal, said second

baseband digital signal corresponding to a converted second RF analog signal received by the second optical repeater;

converting the electrical output signal to an optical output signal; and

transmitting the optical output signal to a base station.

18. (Previously Presented) The method of claim 17, wherein amplifying the RF signals comprises applying a gain to maintain a prescribed amplitude of the amplified RF analog signals in accordance with an automatic gain control (AGC).

19. (Original) The method of claim 17, wherein the first baseband signal is delayed by an amount of delay necessary to match a round trip delay time of at least one second optical repeater.

20. (Original) The method of claim 17, wherein the first optical repeater is a final optical repeater in a series connected chain of optical repeaters.

21. (Previously Presented) The method of claim 17, further comprising receiving an optical input signal from the second optical repeater and converting the optical input signal to the second baseband digital signal.

22. (Original) The method of claim 21, wherein the optical input signal is received from the second optical repeater over an optical cable.

23. (Currently amended) An optical repeater system, comprising:
a first optical repeater configured to receive a first radio frequency (RF) analog signal and output a first baseband digital optical signal;
a second optical repeater coupled to the first optical repeater and configured to receive a second RF analog signal, convert the second RF analog signal to ~~a first~~ a second baseband digital electrical signal, delay ~~the first~~ the second baseband digital electrical signal, convert the first baseband digital optical signal to ~~a second~~ a first baseband digital electrical signal, sum the delayed ~~first~~ second baseband digital electrical signal and the ~~second~~ first baseband digital electrical signal, and convert the summed signal to an output baseband digital optical signal; and
a base station coupled to the second optical repeater and configured to convert the output baseband digital optical signal to a third baseband digital electrical signal and demodulate the third baseband digital electrical signal.

24. (Previously Presented) The system of claim 23, further comprising a third optical repeater configured to receive a third RF analog signal and output a third baseband digital optical

signal, wherein the first optical repeater is configured to convert the first RF analog signal to a fourth baseband digital electrical signal, delay the fourth baseband digital electrical signal, convert the third baseband digital optical signal to a fifth baseband digital electrical signal, sum the delayed fourth baseband digital electrical signal and the fifth baseband digital electrical signal, and convert the sum of the fourth and fifth baseband digital electrical signals to the first baseband digital optical signal.

25. (Previously Presented) The system of claim 23, wherein each of the first and second optical repeaters comprise:

- a band-pass filter (BPF) configured to filter the received RF analog signal and output a filtered RF analog signal;

- an amplifier configured to amplify the filtered RF analog signal with a gain and output an amplified RF analog signal;

- a frequency converter configured to convert the amplified RF analog signal to the first baseband digital electrical signal;

- a digital delay device configured to delay the first baseband digital electrical signal;

- an Optical signal to Electrical signal converter (O/E converter) configured to convert a baseband digital optical signal received from the previous optical repeater to the second baseband digital electrical signal;

a digital summer configured to sum the first baseband digital electrical signal and the second baseband digital electrical signal; and

an Electrical signal to Optical signal digital converter (E/O converter) configured to convert a summed signal outputted from the digital summer to the optical output signal.

26. (Original) An optical repeater system, comprising:

a first optical repeater configured to receive and convert a first radio frequency (RF) signal to a first baseband digital electrical signal and convert the first baseband digital electrical to a first optical signal;

a second optical repeater coupled to receive the first optical signal from the first optical repeater and configured to receive and convert a second RF signal to a second baseband digital electrical signal, convert the first optical signal to an input electrical signal, add the second baseband digital electrical signal to the input electrical signal to generate a summed electrical digital signal, and convert the summed electrical digital signal to a second optical signal; and

a base station configured to receive and demodulate the second optical signal.

27. (Original) The system of claim 26, wherein the first optical repeater is further configured to receive an external optical signal from a third optical repeater, convert the external

optical signal to a second input electrical signal, and sum the second input electrical signal with the first baseband digital electrical signal and convert the sum to the first optical signal.

28. (Original) The system of claim 26, wherein each of the first and second optical repeaters comprise:

- a band-pass filter (BPF) configured to filter the received RF analog signal and output a filtered RF analog signal;

- an amplifier configured to amplify the filtered RF analog signal with a gain and output an amplified RF analog signal;

- a frequency converter configured to convert the amplified RF analog signal to the first baseband digital electrical signal:

- a digital delay device configured to delay the first baseband digital electrical signal;

- an Optical signal to Electrical signal converter (O/E converter) configured to convert a baseband digital optical signal received from the previous optical repeater to the second baseband digital electrical signal;

- a digital summer configured to sum the first baseband digital electrical signal and the second baseband digital electrical signal; and

- an Electrical signal to Optical signal digital converter (E/O converter) configured to convert a summed signal outputted from the digital summer to the optical output signal.

29. (Previously Presented) The system of claim 1, wherein each optical repeater comprises:

an Optical signal converter (O/E converter) to convert a baseband digital optical signal received from the previous optical repeater to the second baseband digital electrical signal;

a digital summer to sum the first baseband digital electrical signal and the second baseband digital electrical signal; and

an Electrical signal to Optical signal digital converter (E/O converter) to convert a summed signal outputted from the digital summer to the optical output signal.

30. (Previously Presented) The system of claim 29, wherein each optical repeater further comprises:

a delay device to delay the first baseband digital electrical signal prior to the optical repeater summing the first baseband digital electrical signal and the second baseband digital electrical signal.